

TRANSFORMER DETAILS:-**USE SPLIT BOBBINE 12 V DESIGN****1. 500VA, 400W, STACK/CORE size 4 No. 2.5 inch CRGO**

PRIMARY	0 - 15 Turn 0 - 8 V	14 SWG X 4 Nos
SECONDARY 1	0 - 520T - 55T 0 - 255V - 270V	22 SWG
SECONDARY 2	0 - 30T 0 - 15V	28 SWG

2. 800VA, STACK/CORE size 4 No. 3.5 inch CRGO

PRIMARY	0 - 11 Turn	13 SWG X 4 Nos
SECONDARY 1	0 - 366T - 380T	21 SWG or 20 SWG
SECONDARY 2	0 - 31T	28 SWG

3. 800VA, STACK/CORE size 4 No. 4 inch CRGO

PRIMARY	0 - 10 Turn	13 SWG X 4 Nos
SECONDARY 1	0 - 320T - 338T	21 SWG or 20 SWG
SECONDARY 2	0 - 19T	28 SWG

4. 800VA, STACK/CORE size 7 No. 2 inch CRGO Core thickness .35

PRIMARY	0 - 13 Turn/15V	11 SWG X 3 Nos
SECONDARY 1	0 - 340T - 360T	19 SWG
SECONDARY 2	0 - 20T / 15V	25 SWG